



Power-Save Fluorescent Light Manager

Product Specifications

Model 01 (Single Pole)

Description:

The Power-Save Fluorescent Light Manager (FLM) is ideal for those seeking easy installation, comfort from harsh lighting environments, the ability to control various light sources, and energy savings. The Power-Save Fluorescent Light Manager does it all. The Power-Save Fluorescent Light Manager can control Compact Fluorescent lights (non-dimmable and dimmable), Linear Fluorescent tubes (T12, T8, T5, circular) with standard electronic and magnetic ballasts, Cold Cathode lamps, Halogen, and Incandescent. Step down dimming allows you to set your personal preferences. Memory is protected during temporary power failures.

Easy to install

AC power failure correction mode

Micro-Processor controls various light sources

Memory of last setting level – when turned off and on again, automatically sets to last level

Specifications:

Assembled Unit Depth (in inches): 2.13"

Unit Height (in inches): 4.12"

Unit Width (in inches): 2.11"

Commercial/Residential: Both

Maximum Amperage: 3 AMP

Product Features:

Model Name: FLM-01

Switch Type: Single Pole

Type: Digital

Load Type: Resistive, Inductive, Capacitive

Load Rating: 300W / 150W CFL

Voltage: 120V AC 60 Hz

Warranty: 1 year limited

Standards and Certifications: ETL/CSA

GFI Compatible

Color: White

